

APR-1- RM

AUDIO BASE STATION (Rack Mounted)

TECHNICAL DATA SHEET

DESCRIPTION

The APR-1-RM is a rack mounted single zone audio base station designed to interface with a DVR, VCR or other recording devices that accept line level input. The APR-1 Audio Base Station contains a built-in 3" speaker and volume control for producing live audio and audio playback. Has mute switch to mute audio from being heard at the speaker.



APR-1-RM Audio Base Station



AD-1 Power Supply



DUAL RCA Cable

CONTENTS

- APR-1-RM Listed Audio Base Station (Rack Mounted).
- AD-1 Listed AC Adapter
- Dual RCA Cable

FEATURES

- Audio output (RCA) to DVR, VCR
- 3" speaker for monitoring live audio and playback from a DVR or VCR
- 3.5 mm headphone jack for private listening
- Mute switch to mute audio from being heard at the speaker
- Overload LED to indicate short in wiring connections

APPLICATION

The APR-1-RM is designed for numerous applications such as:

- Convenience Stores
- Fast Food Restaurants
- Booking Rooms
- Interrogation Rooms
- Car dealership sales contract rooms
- Child Abuse Interviews
- Sleep Disorder Centers
- Speech Therapy Labs
- Cashier Booths
- Casino use in:
 - soft count rooms
 - detention centers
 - medical treatment rooms
 - cash cages

SPECIFICATIONS (Base Station - APR-1)

■ Monitor output power	1W@8Ω
■ Audio line output impedance	600Ω or higher
■ Audio input impedance	10KΩ
■ Freq. response	100 Hz to 10 kHz
■ Headphone impedance	8 to 600Ω
■ Universal power supply	12 Vdc, 500 mA
■ Dimensions	19"L x 3 1/2"W x 8 1/4"D
■ Weight	2 lb 6 oz
■ Shipping Weight	4 lbs

WIRING REQUIREMENTS

2 Conductor **shielded** cable, 22 gauge with a 24 gauge drain wire.

NOTE: Unshielded cable is not satisfactory for audio systems.

West Penn 452 or equivalent

